

North Queensland System Strength Constraints

Disclaimer: This document or the information in it is current at the time of publication but may be subsequently updated or amended. This document does not constitute legal or business advice, and should not be relied on as a substitute for obtaining detailed advice about the National Electricity Law, the National Electricity Rules, or any other applicable laws, procedures or policies. Powerlink has made every effort to ensure the quality of the information in this document but cannot guarantee its accuracy or completeness.

Accordingly, to the maximum extent permitted by law, Powerlink and its employees involved in the preparation of this document:

- make no representation or warranty, express or implied, as to the currency, accuracy, reliability or completeness of the information in this document; and
- are not liable (whether by reason of negligence or otherwise) for any statements or representations in this document, or any omissions from it, or for any use or reliance on the information in it.

Version Control

Version	Release date	Changes
1	9 September 2020	Initial version
2	7 October 2020	Added five new combinations (5e, 7c, 7d, 8a.1 and 8a.2)
3	9 November 2020	Constraints modified as a result of updated settings at Mt Emerald WF.
		Deleted 1, 2, 3, 4, 6, 7a-b and 8b-c.
		Added 10, 11 and 12.
4	24 November 2020	Added two new combinations 10b and 11c.
5	11 December 2020	Updated 11c.
6	1 June 2021	Deleted 5a-e, 7c-d, 8a,a.1,a.2, 10a-b, 11a-c, 12a-b
		Added 9a.1, 9a.2, 9c, 13
		Modified 9b
7	5 August 2021	Modified 9b
8	20 August 2021	Added 14
9	26 November 2021	Deleted 9a and 9a.1
		Added 9a.3, 9a.4 and 9b.1
10	16 August 2022	Added 15
11	30 September 2022	Deleted 9a.2, 9b, 9c, 13 and 14
		Added 16-21 to include Kaban WF while 3 rd 275kV feeder 8905 between Ross and Woree is not operational
12	13 February 2023	Deleted 9a.3, 9a.4, 9b.1 and 15
		Added 16a.1, 16a.2
13	01 August 2023	Updated 17 and 20 to reflect 3 rd 275kV feeder 8905 between Ross and Woree is operational
14	05 January 2024	Updated 16 and 16a.1
15	08 October 2024	Updated Table 1 to include Clarke Creek WF
16	31 January 2025	Updated Table 1 to remove the column with Gladstone ≥ 1
17	29 August 2025	Updated Table 1 to include Townsville GT1 and formatting changes (removing, merging, and re-numbering rows).

EDRMS A3424409

NQLD system strength constraints

Table of Contents

1	Introduction	. 3
2	Constraints	. 3

1 Introduction

System strength is a measure of the stability of a power system under all reasonably possible operating conditions. It describes a system's overall performance and its ability to recover quickly from sudden events.

System strength affects the stability and dynamics of generating systems' control systems, and the ability of the power system to both:

- Remain stable under normal conditions, and
- Return to steady-state conditions following a disturbance (such as a fault).

This document describes the constraints on North Queensland Inverter Based Renewable (IBR) generation due to system strength under system normal conditions.

2 Constraints

Table 1 summarises the combinations of the synchronous generating units and associated constraints on IBR plants in North Queensland (NQLD).

The PSCAD model extends from Far North Queensland to the Hunter Valley in New South Wales (NSW). It includes plant specific models for IBR and synchronous generators (including voltage control systems) and transmission connected dynamic voltage control plant (Static Var Compensators and Statcoms). All the IBR generators connected to the transmission network have been considered in this analysis. IBR generators larger than 40MW and connected to the distribution network have also been taken into consideration in the assessment.

The PSCAD analysis revealed that the load level in NQLD impacts the hosting capacity of the IBR generation in the area. Different loading levels were studied for different generation dispatches in NQLD.

The NQLD load is measured as sum of Scheduled and Semi scheduled generation north of Central Queensland – North Queensland (CQ-NQ) grid-section and CQ - NQ Northerly transfer.

NQLD system strength constraints

The Ross and Far North Queensland (FNQ) load is measured as sum of Scheduled and Semi scheduled generation north of Ross cut-set and Ross cut-set Northerly transfer. Ross cut-set is defined across

- Ross Strathmore 275kV feeders, and
- Clare South Strathmore 132kV feeder, and
- Clare South King Creek 132kV feeder.

The following tables describe limit equations for the IBRs in NQLD. The Boolean AND operation is applied to the system conditions across a row. If the expression yields a 'True' value then the maximum capacity quoted for the farm in question becomes an argument to a MAX function. If 'False' then zero (0) becomes the argument to the MAX function. The maximum capacity is the result of the MAX function.

Under some network conditions (including the system conditions not meeting the requirements listed in the table below), generating plants are required to disconnect all the inverters/turbines to avoid the adverse system strength impact (disconnection can be achieved by completely stopping firing of power electronics switches at inverters/turbines). The requirement for inverter/turbine disconnection for a generating plant is communicated real time through NEMDE via a system strength constrain ID.

NQLD system strength constraints

Table 1 System strength constraint when the third 275kV feeder 8905 between Ross and Woree is operational

No.	Stanwell	Total of Stanwell + Callide	Total of Stanwell + Callide + Gladstone	Kareeya	Svnchronous	Synchronous Condenser	NOLD	Ross + FNQ Load	Clarke Creek WF (MW)	Haughton SF (MW)	Kaban WF (MW)	Mt Emerald	Other NQLD plants (MW) (Note 3)	
	≥2	≥3	≥7	≥0	≥1	ON	>250MW	>100MW	100%	100% (if Haughton Syn		100%	100%	Day/Night*
22										Con ON)	100%			
										50% (if Haughton				
										Syn Con OFF)				
	≥2	≥3	≥7	≥2	≥0	ON	>350MW	>150MW	100%	100% (if		100%	100%	Day/Night*
										Haughton Syn	100%			
23										Con ON)				
										50% (if Haughton				
										Syn Con OFF)				
	≥1	≥4	≥6	≥2	≥0	ON	>350MW	>150MW	/ 100%	100% (if		100%	100%	Day/Night*
										Haughton Syn	100%			
24										Con ON)				
										50% (if Haughton				
										Syn Con OFF)				
25	≥1	≥4	≥6	≥0	≥2	ON	>250MW	>100MW	100%	100%	100%	100%	100%	Day/Night*

EDRMS A3424409 5

No	Stanwell	Total of Stanwell + Callide	Total of Stanwell + Callide + Gladstone	Kareeya	Synchronous	Synchronous Condenser		Ross + FNQ Load	Clarke Creek WF (MW)	Haughton SF (MW)	Kaban WF (MW)	Mt Emerald	Other NQLD plants (MW) (Note 3)	
	≥2	≥3	≥7	≥0	≥1	OFF	>250MW	>100MW	0% (Note 1)	100% (if Haughton Syn		100%	100%	Day/Night*
26										Con ON) 50% (if Haughton	100%			
										Syn Con OFF)				
	≥2	≥3	≥7	≥2	≥0	OFF	>350MW	MW >150MW	N 0% (Note 1)	100% (if Haughton Syn	100%	100%	100%	Day/Night*
27										Con ON)				
										50% (if Haughton				
										Syn Con OFF)				
	≥1	≥4	≥6	≥2	≥1	OFF	>350MW	>150MW	W 0% (Note 1)	100% (if				
										Haughton Syn	100% 100			
28										Con ON)		100%	100%	Day/Night*
										50% (if Haughton				
										Syn Con OFF)				
29	≥1	≥4	≥6	≥0	≥2	OFF	>250MW	>100MW	0% (Note 1)	100%	100%	100%	100%	Day/Night*

^{* &#}x27;Night' conditions refer to the total solar horizontal irradiance at Sun Metals, Haughton, Clare and Ross River < 4 and there are no inverters online at Solar Farms.

EDRMS A3424409 6

Note 1: All inverters/turbines should be disconnected.

Note 2: This includes where Townsville GT1 is either operating in generation mode (generating) or in synchronous condenser mode.

Note 3: Other NQLD plants include Clare Solar Farm, Ross River Solar Farm, Sun Metals Solar Farm, Hamilton Solar Farm, Whitsunday Solar Farm, Daydream Solar Farm, Hayman Solar Farm, Collinsville Solar Farm, Kidston Solar Farm, Rugby Run Solar Farm, and Kennedy Energy Park.